


Enclosed Non-Reversing Combination Controller, AC Operation - Type 1/12K/IP66 ⑥⑦

Amp / Horsepower Rating				Non-Metallic Type 1/12K/IP66 Enclosure (KS7-COC4R)					
									
Max. Horsepower ①②③				O/L Relay Ampere Range	Magnetic Response Current	Index ④	Catalog Number ⑤⑥⑦⑧	Price	Dimension Code
Three Phase									
200V	230V	460V	575V						
KTA7-25S Standard Interrupting Capacity									
~	~	~	~	0.10...0.16	2.1	1	CX7-9-10-AS0.16A-A10-PG▼	518.15	Q4
~	~	~	~	0.16...0.25	3.3	2	CX7-9-10-AS0.25A-A10-PG▼	518.15	Q4
~	~	~	~	0.25...0.40	5.2	3	CX7-9-10-AS0.4A-A10-PG▼	518.15	Q4
~	~	~	~	0.40...0.63	8.2	4	CX7-9-10-AS0.63A-A10-PG▼	543.70	Q4
~	~	1/2	3/4	0.63...1.0	13	5	CX7-9-10-AS1A-A10-PG▼	543.70	Q4
~	~	1	1	1.0...1.6	21	6	CX7-9-10-AS1.6A-A10-PG▼	543.70	Q4
1/2	3/4	1-1/2	2	1.6...2.5	33	7	CX7-9-10-AS2.5A-A10-PG▼	543.70	Q4
1	1	3	3	2.5...4	52	8	CX7-9-10-AS4A-A10-PG▼	543.70	Q4
1-1/2	2	5	~	4...6.3	82	9	CX7-9-10-AS6.3A-A10-PG▼	543.70	Q4
3	3	7-1/2	~	6.3...10	130	11	CX7-12-10-AS10A-A10-PG▼	583.56	Q4
5	5	10	~	10...16	208	12	CX7-16-10-AS16A-A10-PG▼	594.80	Q4
5	7-1/2	15	~	14.5...20	260	15	CX7-23-10-AS20A-A10-PG▼	654.08	Q4
KTA7-25H High Interrupting Capacity									
1/2	3/4	1-1/2	2	1.6...2.5	33	17	CX7-9-10-AH2.5A-A10-PG▼	600.94	Q4
1	1	3	3	2.5...4	52	19	CX7-9-10-AH4A-A10-PG▼	600.94	Q4
1-1/2	2	5	5	4...6.3	82	22	CX7-9-10-AH6.3A-A10-PG▼	600.94	Q4
3	3	7-1/2	10	6.3...10	130	24	CX7-12-10-AH10A-A10-PG▼	656.12	Q4
5	5	10	15	10...16	208	28	CX7-16-10-AH16A-A10-PG▼	685.76	Q4
5	7-1/2	15	~	14.5...20	260	31	CX7-23-10-AH20A-A10-PG▼	710.29	Q4
5	7-1/2	15	~	18...25	325	33	CX7-23-10-AH25A-A10-PG▼	710.29	Q4

Includes:

- Type 1/12K Non-metallic enclosure (KS7-COC4R)
- KTA7 "Type E/F" Self-protected Combination Motor Controller with 1 NO front mount Auxiliary Contact (Cat #: KT7-PE1-10)
- Terminal Adaptor for Type E Applications (Cat.# KT7-25-TE1)
- CA7 contactor (for remote operation), AC coil
- Gray and black Type 1/12K; IP66 handle (KT7-SHB + KT7-KN1) ③
- Power wiring
- Factory installed Pilot device option ⑥

*Replace ▼ with option code.
See page F103 for
factory installed modifications*

Contactor

AC Coil Codes (*) ④


AC Coil Code	Voltage Range	
	50 Hz	60 Hz
24Z	24V	24V
120	110V	120V
220W	200V-220V	208V-240V
240	220V	240V
480 ⑤	440V	480V
600 ⑥	550V	600V

KWIKstarter coils are wired standard from the factory to terminals "L1" and "L2" (for line voltage control). This means the coil voltage must match the line voltage. When a coil is specified for 120V or less, it will be wired for a separate control source (not wired to L1 and L2).

- ① Horsepower ratings shown in the table above are for reference. **The final selection of the controller depends on the actual motor full load current and service factor.** For motor with service factor less than 1.15. Use motor nameplate full load current times 0.9 and choose the motor starter with the appropriate current range. Example: Motor FLC = 4.2A; S.F. = 1.0. 4.2A x 0.9 = 3.78A. Select catalog number KTA7-25S-4A.
- ② Magnetic trip is fixed at 13x the maximum value of the current adjustment range.
- ③ CX7 may be applied to single phase loads. Contact factory for these specifications.
- ④ Other voltages available, see Section A in this catalog.
- ⑤ KAIC Assembly Rating Index. See pages F73-F76 for Application Rating Guide.
- ⑥ One Pilot Device option must be selected. Plastic Bezel is standard. Pilot Device options include D7-BX_ Base Mounted contact blocks. Pilot Light option must match coil voltage 24V AC or DC, 120V AC or 240V AC only. See Section H for more information.

- ⑦ CPT not possible with KS7-COC4R. Refer to page F118 for wiring diagram and F119 for dimensional information.
- ⑧ A red and yellow handle may be selected instead of the standard gray and black handle. Change "PG" suffix to "PJ". Ex: Change CX7-9-10-AS0.16A-A10-PG▼ to CX7-9-10-AS0.16A-A10-PJ▼.
- ⑨ Catalog number (-A10) includes front-mounted auxiliary KT7-PE1-10 with 300 VAC maximum control circuit matching line voltage, or provided from separate source, used to de-energize contactor coil under fault condition (auxiliary not available for customer use). For control circuits greater than 300 VAC, which is common with line voltage, the auxiliary will not be wired into the control circuit since the contactor coil will be de-energized when KTA7 is tripped due to overload or short circuit; therefore, the KT7-PE1-10 auxiliary is available for customer use.

Enclosed Non-Reversing Combination Controller, Electronic DC Operation - Type 1/12K/IP66 ④⑥⑦

Amp / Horsepower Rating				Non-Metallic Type 1/12K/IP66 Enclosure (KS7-COC4R)					
									
Max. Horsepower ①②③				O/L Relay Ampere Range	Magnetic Response Current	Index ⑤	Catalog Number ④⑥⑧	Price	Dimension Code
Three Phase									
200V	230V	460V	575V						
KTA7-25S Standard Interrupting Capacity									
~	~	~	~	0.10...0.16	2.1	1	CX7-9E-10- * -AS0.16A-A10-PG▼	565.17	Q4
~	~	~	~	0.16...0.25	3.3	2	CX7-9E-10- * -AS0.25A-A10-PG▼	565.17	Q4
~	~	~	~	0.25...0.40	5.2	3	CX7-9E-10- * -AS0.4A-A10-PG▼	590.72	Q4
~	~	~	~	0.40...0.63	8.2	4	CX7-9E-10- * -AS0.63A-A10-PG▼	590.72	Q4
~	~	1/2	3/4	0.63...1.0	13	5	CX7-9E-10- * -AS1A-A10-PG▼	590.72	Q4
~	~	1	1	1.0...1.6	21	6	CX7-9E-10- * -AS1.6A-A10-PG▼	590.72	Q4
1/2	3/4	1-1/2	2	1.6...2.5	33	7	CX7-9E-10- * -AS2.5A-A10-PG▼	590.72	Q4
1	1	3	3	2.5...4	52	8	CX7-9E-10- * -AS4A-A10-PG▼	590.72	Q4
1-1/2	2	5	~	4...6.3	82	9	CX7-9E-10- * -AS6.3A-A10-PG▼	590.72	Q4
3	3	7-1/2	~	6.3...10	130	11	CX7-12E-10- * -AS10A-A10-PG▼	630.57	Q4
5	5	10	~	10...16	208	12	CX7-16E-10- * -AS16A-A10-PG▼	641.82	Q4
5	7-1/2	15	~	14.5...20	260	15	CX7-23E-10- * -AS20A-A10-PG▼	701.09	Q4
KTA7-25H High Interrupting Capacity									
1/2	3/4	1-1/2	2	1.6...2.5	33	17	CX7-9E-10- * -AH2.5A-A10-PG▼	647.95	Q4
1	1	3	3	2.5...4	52	19	CX7-9E-10- * -AH4A-A10-PG▼	647.95	Q4
1-1/2	2	5	5	4...6.3	82	22	CX7-9E-10- * -AH6.3A-A10-PG▼	647.95	Q4
3	3	7-1/2	10	6.3...10	130	24	CX7-12E-10- * -AH10A-A10-PG▼	701.09	Q4
5	5	10	15	10...16	208	28	CX7-16E-10- * -AH16A-A10-PG▼	732.77	Q4
5	7-1/2	15	~	14.5...20	260	31	CX7-23E-10- * -AH20A-A10-PG▼	757.30	Q4
5	7-1/2	15	~	18...25	325	33	CX7-23E-10- * -AH25A-A10-PG▼	757.30	Q4

Includes:

- Type 1/12K Non-metallic enclosure (KS7-COC4R)
- KTA7 "Type E/F" Self-protected Combination Motor Controller with 1 NO front mount Auxiliary Contact (Cat #: KT7-PE1-10)
- Terminal Adaptor for Type E Applications (Cat.# KT7-25-TE1)
- CA7 contactors (for remote operation), with Electronic DC Coil
- Gray and black Type 1/12K; IP66 handle (KT7-SHB) + KT7-KN1 ⑧
- Power wiring
- Factory installed Pilot device option ⑥

*Replace ▼ with option code.
See page F103 for
factory installed modifications*

Contactor Electronic DC Coil Codes (*) ④

DC Coil Codes	Voltage
12E	12V
24E	24V
36E	36-48V
48E	48-72V
110E	110-125V
220E	220-250V

KWIKstarter coils are wired standard from the factory to terminals "L1" and "L2" (for line voltage control). This means the coil voltage must match the line voltage. When a coil is specified for 120V or less, it will be wired for a separate control source (not wired to L1 and L2).

- ① Horsepower ratings shown in the table above are for reference. The final selection of the controller depends on the actual motor full load current and service factor. For motor with service factor less than 1.15. Use motor nameplate full load current times 0.9 and choose the motor starter with the appropriate current range. Example: Motor FLC = 4.2A; S.F. = 1.0. 4.2A x 0.9 = 3.78A. Select catalog number KTA7-25S-4A.
- ② Magnetic trip is fixed at 13x the maximum value of the current adjustment range.
- ③ CX7 may be applied to single phase loads. Contact factory for these specifications.
- ④ CX7-9E...23E with electronic coils are not interchangeable with non-electronic DC or AC coils.
- ⑤ KAIC Assembly Rating Index. See pages F73-F76 for Application Rating Guide.

- ⑥ One Pilot Device option must be selected. Plastic Bezel is standard. Pilot Device options include D7-BX_ Base Mounted contact blocks. Pilot Light option must match coil voltage 24V AC or DC, 120V AC or 240V AC only. See Section H for more information.
- ⑦ CPT not possible with KS7-COC4R. Refer to page F118 for wiring diagram and F119 for dimensional information.
- ⑧ A red and yellow handle may be selected instead of the standard gray and black handle. Change "PG" suffix to "PJ". Ex: Change CX7-9-10-*****-AS0.16A-A10-PG▼ to CX7-9-10-*****-AS0.16A-A10-PJ▼.

Enclosed Non-Reversing Combination Controller with E-Stop, AC Operation - Type 1/12K/IP66 ①⑦⑧

Amp / Horsepower Rating				Non-Metallic Type 1/12K/IP66 Enclosure (KS7-C0C4R)						
				Max. Horsepower ②③④				O/L Relay Ampere Range	Magnetic Response Current	Index ⑤
Three Phase										
200V	230V	460V	575V							
KTA7-25S Standard Interrupting Capacity										
~	~	~	~	0.10...0.16	2.1	1	CX7-9-10-*AS0.16A-A10-PG4U-9	607.07	Q4	
~	~	~	~	0.16...0.25	3.3	2	CX7-9-10-*AS0.25A-A10-PG4U-9	607.07	Q4	
~	~	~	~	0.25...0.40	5.2	3	CX7-9-10-*AS0.4A-A10-PG4U-9	607.07	Q4	
~	~	~	~	0.40...0.63	8.2	4	CX7-9-10-*AS0.63A-A10-PG4U-9	607.07	Q4	
~	~	1/2	3/4	0.63...1.0	13	5	CX7-9-10-*AS1A-A10-PG4U-9	607.07	Q4	
~	~	1	1	1.0...1.6	21	6	CX7-9-10-*AS1.6A-A10-PG4U-9	607.07	Q4	
1/2	3/4	1-1/2	2	1.6...2.5	33	7	CX7-9-10-*AS2.5A-A10-PG4U-9	607.07	Q4	
1	1	3	3	2.5...4	52	8	CX7-9-10-*AS4A-A10-PG4U-9	607.07	Q4	
1-1/2	2	5	~	4...6.3	82	9	CX7-9-10-*AS6.3A-A10-PG4U-9	607.07	Q4	
3	3	7-1/2	~	6.3...10	130	11	CX7-12-10-*AS10A-A10-PG4U-9	671.45	Q4	
5	5	10	~	10...16	208	12	CX7-16-10-*AS16A-A10-PG4U-9	682.70	Q4	
5	7-1/2	15	~	14.5...20	260	15	CX7-23-10-*AS20A-A10-PG4U-9	741.97	Q4	
KTA7-25H High Interrupting Capacity										
1/2	3/4	1-1/2	2	1.6...2.5	33	17	CX7-9-10-*AH2.5A-A10-PG4U-9	689.85	Q4	
1	1	3	3	2.5...4	52	19	CX7-9-10-*AH4A-A10-PG4U-9	689.85	Q4	
1-1/2	2	5	5	4...6.3	82	22	CX7-9-10-*AH6.3A-A10-PG4U-9	689.85	Q4	
3	3	7-1/2	10	6.3...10	130	24	CX7-12-10-*AH10A-A10-PG4U-9	747.08	Q4	
5	5	10	15	10...16	208	28	CX7-16-10-*AH16A-A10-PG4U-9	774.68	Q4	
5	7-1/2	15	~	14.5...20	260	31	CX7-23-10-*AH20A-A10-PG4U-9	799.20	Q4	
5	7-1/2	15	~	18...25	325	33	CX7-23-10-*AH25A-A10-PG4U-9	799.20	Q4	



Includes:

- Type 1/12K Non-metallic enclosure (KS7-C0C4R) ①
- KTA7 "Type E/F" Self-protected Combination Motor Controller with 1 NO front mount Auxiliary Contact (Cat #: KT7-PE1-10)
- Terminal Adaptor for Type E Applications (Cat.# KT7-25-TE1)
- CA7 contactor (for remote operation), AC coil
- Multifunction 2-position Push Button and Emergency Stop ⑦
- Gray and black Type 1/12K; IP66 handle (KT7-SHB + KT7-KN1) ⑧
- Power wiring

This is a factory assembly.
Optional factory modifications are not available on this device.

**Contactor
AC Coil Codes (*) ⑤**

AC Coil Code	Voltage Range	
	50 Hz	60 Hz
24Z	24V	24V
120	110V	120V
220W	200V-220V	208V-240V
240	220V	240V
480 ⑩	440V	480V
600 ⑩	550V	600V

KWIKstarter coils are wired standard from the factory to terminals "L1" and "L2" (for line voltage control). This means the coil voltage must match the line voltage. When a coil is specified for 120V or less, it will be wired for a separate control source (not wired to L1 and L2).


- ① This is a factory assembly. The KS7-C0C4R does not include knock-outs for field assembly of this starter.
- ② Horsepower ratings shown in the table above are for reference. The final selection of the controller depends on the actual motor full load current and service factor. For motor with service factor less than 1.15. Use motor nameplate full load current times 0.9 and choose the motor starter with the appropriate current range. Example: Motor FLC = 4.2A; S.F. = 1.0. 4.2A x 0.9 = 3.78A. Select catalog number KTA7-25S-4A.
- ③ Magnetic trip is fixed at 13x the maximum value of the current adjustment range.
- ④ CX7 may be applied to single phase loads. Contact factory for these specifications.
- ⑤ Other voltages available, see Section A in this catalog.
- ⑥ KAIC Assembly Rating Index. See pages F73-F76 for Application Rating Guide.
- ⑦ Uses D7P-U2EFFEPX11 Two-Position Multifunction push button with legend I/O and D7P-MT44PX01 Emergency Stop Push Button.

- ⑧ CPT not possible with KS7-C0C4R. Refer page F119 for dimensional information.
- ⑨ A red and yellow handle may be selected instead of the standard gray and black handle. Change "PG" suffix to "PJ". Ex: CX7-9-10-*AS0.16A-A10-PG4U-9 becomes CX7-9-10-*AS0.16A-A10-PJ4U-9.
- ⑩ Catalog number (-A10) includes front-mounted auxiliary KT7-PE1-10 with 300 VAC maximum control circuit matching line voltage, or provided from separate source, used to de-energize contactor coil under fault condition (auxiliary not available for customer use). For control circuits greater than 300 VAC, which is common with line voltage, the auxiliary will not be wired into the control circuit since the contactor coil will be de-energized when KTA7 is tripped due to overload or short circuit; therefore, the KT7-PE1-10 auxiliary is available for customer use.

Enclosed Reversing Combination Controller, AC Operation - Type 1/12K/IP66 ⑥⑦

Amp / Horsepower Rating				Non-Metallic Type 1/12K/IP66 Enclosure (KS7-COC4R)						
Max. Horsepower ①②③				O/L Relay Ampere Range	Magnetic Response Current	Index ④	Catalog Number ⑤⑥⑦⑧	Price	Dimension Code	
Three Phase										
200V	230V	460V	575V	KTA7-25S Standard Interrupting Capacity						
~	~	~	~	0.10...0.16	2.1	1	CXU7-9-22-*AS0.16A-A10-PG▼	803.29	Q4	
~	~	~	~	0.16...0.25	3.3	2	CXU7-9-22-*AS0.25A-A10-PG▼	803.29	Q4	
~	~	~	~	0.25...0.40	5.2	3	CXU7-9-22-*AS0.4A-A10-PG▼	803.29	Q4	
~	~	~	~	0.40...0.63	8.2	4	CXU7-9-22-*AS0.63A-A10-PG▼	828.84	Q4	
~	~	1/2	3/4	0.63...1.0	13	5	CXU7-9-22-*AS1A-A10-PG▼	828.84	Q4	
~	~	1	1	1.0...1.6	21	6	CXU7-9-22-*AS1.6A-A10-PG▼	828.84	Q4	
1/2	3/4	1-1/2	2	1.6...2.5	33	7	CXU7-9-22-*AS2.5A-A10-PG▼	828.84	Q4	
1	1	3	3	2.5...4	52	8	CXU7-9-22-*AS4A-A10-PG▼	828.84	Q4	
1-1/2	2	5	~	4...6.3	82	9	CXU7-9-22-*AS6.3A-A10-PG▼	828.84	Q4	
3	3	7-1/2	~	6.3...10	130	11	CXU7-12-22-*AS10A-A10-PG▼	899.36	Q4	
5	5	10	~	10...16	208	12	CXU7-16-22-*AS16A-A10-PG▼	935.13	Q4	
5	7-1/2	15	~	14.5...20	260	15	CXU7-23-22-*AS20A-A10-PG▼	959.66	Q4	
				KTA7-25H High Interrupting Capacity						
1/2	3/4	1-1/2	2	1.6...2.5	33	17	CXU7-9-22-*AH2.5A-A10-PG▼	886.07	Q4	
1	1	3	3	2.5...4	52	19	CXU7-9-22-*AH4A-A10-PG▼	886.07	Q4	
1-1/2	2	5	5	4...6.3	82	22	CXU7-9-22-*AH6.3A-A10-PG▼	886.07	Q4	
3	3	7-1/2	10	6.3...10	130	24	CXU7-12-22-*AH10A-A10-PG▼	971.92	Q4	
5	5	10	15	10...16	208	28	CXU7-16-22-*AH16A-A10-PG▼	1,001.56	Q4	
5	7-1/2	15	~	14.5...20	260	31	CXU7-23-22-*AH20A-A10-PG▼	1,026.09	Q4	
5	7-1/2	15	~	18...25	325	33	CXU7-23-22-*AH25A-A10-PG▼	1,026.09	Q4	

Non-Metallic Type 1/12K/IP66 Enclosure (KS7-COC4R)



Includes:

- Type 1/12K Non-metallic enclosure (KS7-COC4R)
- KTA7 "Type E/F" Self-protected Combination Motor Controller with 1 NO front mount Auxiliary Contact (Cat #: KT7-PE1-10)
- Terminal Adaptor for Type E Applications (Cat.# KT7-25-TE1)
- CA7 contactor (for remote operation), AC coil
- Gray and black Type 1/12K; IP66 handle (KT7-SHB + KT7-KN1) ③
- Power wiring
- Factory installed Pilot device option ⑥

Replace ▼ with option code.
See page F103 for factory installed modifications

Contactor

AC Coil Codes (*) ④


AC Coil Code	Voltage Range	
	50 Hz	60 Hz
24Z	24V	24V
120	110V	120V
220W	200V-220V	208V-240V
240	220V	240V
480 ⑤	440V	480V
600 ⑤	550V	600V

KWIKstarter coils are wired standard from the factory to terminals "L1" and "L2" (for line voltage control). This means the coil voltage must match the line voltage. When a coil is specified for 120V or less, it will be wired for a separate control source (not wired to L1 and L2).

- ① Horsepower ratings shown in the table above are for reference. The final selection of the controller depends on the actual motor full load current and service factor. For motor with service factor less than 1.15. Use motor nameplate full load current times 0.9 and choose the motor starter with the appropriate current range. Example: Motor FLC = 4.2A; S.F. = 1.0. 4.2A x 0.9 = 3.78A. Select catalog number KTA7-25S-4A.
- ② Magnetic trip is fixed at 13x the maximum value of the current adjustment range.
- ③ CXU7 may be applied to single phase loads. Contact factory for specifications.
- ④ Other voltages available, see Section A in this catalog.
- ⑤ KAIC Assembly Rating Index. See pages F73-F76 for Application Rating Guide.
- ⑥ One Pilot Device option must be selected. Plastic Bezel is standard. Pilot Device options include D7-BX_ Base Mounted contact blocks. Pilot Light option must match coil voltage 24V AC or DC, 120V AC or 240V AC only. See Section H for more information.

- ⑦ CPT not possible with KS7-COC4R. Refer to page F118 for wiring diagram and F119 for dimensional information.
- ⑧ A red and yellow handle may be selected instead of the standard gray and black handle. Change "PG" suffix to "PJ". Ex: Change CXU7-9-10-*AS0.16A-A10-PG▼ to CXU7-9-10-*AS0.16A-A10-PJ▼.
- ⑨ Catalog number (-A10) includes front-mounted auxiliary KT7-PE1-10 with 300 VAC maximum control circuit matching line voltage, or provided from separate source, used to de-energize contactor coil under fault condition (auxiliary not available for customer use). For control circuits greater than 300 VAC, which is common with line voltage, the auxiliary will not be wired into the control circuit since the contactor coil will be de-energized when KTA7 is tripped due to overload or short circuit; therefore, the KT7-PE1-10 auxiliary is available for customer use.

Enclosed Reversing Combination Controller, Electronic DC Operation - Type 1/12K/IP66 ④⑥⑦

Amp / Horsepower Rating				Non-Metallic Type 1/12K/IP66 Enclosure (KS7-COC4R)					
Max. Horsepower ①②③				O/L Relay Ampere Range	Magnetic Response Current	Index ⑤	Catalog Number ④⑥⑦	Price	Dimension Code
Three Phase									
200V	230V	460V	575V						
KTA7-25S Standard Interrupting Capacity									
~	~	~	~	0.10...0.16	2.1	1	CXU7-9E-22-*AS0.16A-A10-PG▼	897.32	Q4
~	~	~	~	0.16...0.25	3.3	2	CXU7-9E-22-*AS0.25A-A10-PG▼	897.32	Q4
~	~	~	~	0.25...0.40	5.2	3	CXU7-9E-22-*AS0.4A-A10-PG▼	922.87	Q4
~	~	~	~	0.40...0.63	8.2	4	CXU7-9E-22-*AS0.63A-A10-PG▼	922.87	Q4
~	~	1/2	3/4	0.63...1.0	13	5	CXU7-9E-22-*AS1A-A10-PG▼	922.87	Q4
~	~	1	1	1.0...1.6	21	6	CXU7-9E-22-*AS1.6A-A10-PG▼	922.87	Q4
1/2	3/4	1-1/2	2	1.6...2.5	33	7	CXU7-9E-22-*AS2.5A-A10-PG▼	922.87	Q4
1	1	3	3	2.5...4	52	8	CXU7-9E-22-*AS4A-A10-PG▼	922.87	Q4
1-1/2	2	5	~	4...6.3	82	9	CXU7-9E-22-*AS6.3A-A10-PG▼	922.87	Q4
3	3	7-1/2	~	6.3...10	130	11	CXU7-12E-22-*AS10A-A10-PG▼	993.38	Q4
5	5	10	~	10...16	208	12	CXU7-16E-22-*AS16A-A10-PG▼	1,029.15	Q4
5	7-1/2	15	~	14.5...20	260	15	CXU7-23E-22-*AS20A-A10-PG▼	959.66	Q4
KTA7-25H High Interrupting Capacity									
1/2	3/4	1-1/2	2	1.6...2.5	33	17	CXU7-9E-22-*AH2.5A-A10-PG▼	980.10	Q4
1	1	3	3	2.5...4	52	19	CXU7-9E-22-*AH4A-A10-PG▼	980.10	Q4
1-1/2	2	5	5	4...6.3	82	22	CXU7-9E-22-*AH6.3A-A10-PG▼	980.10	Q4
3	3	7-1/2	10	6.3...10	130	24	CXU7-12E-22-*AH10A-A10-PG▼	1,065.95	Q4
5	5	10	15	10...16	208	28	CXU7-16E-22-*AH16A-A10-PG▼	1,096.61	Q4
5	7-1/2	15	~	14.5...20	260	31	CXU7-23E-22-*AH20A-A10-PG▼	1,120.11	Q4
5	7-1/2	15	~	18...25	325	33	CXU7-23E-22-*AH25A-A10-PG▼	1,120.11	Q4

Includes:

- Type 1/12K Non-metallic enclosure (KS7-COC4R)
- KTA7 "Type E/F" Self-protected Combination Motor Controller with 1 NO front mount Auxiliary Contact (Cat #: KT7-PE1-10)
- Terminal Adaptor for Type E Applications (Cat.# KT7-25-TE1)
- CA7 contactors (for remote operation), with Electronic DC coil
- Gray and black Type 1/12K; IP66 handle (KT7-SHB + KT7-KN1) ③
- Power wiring
- Factory installed Pilot device option ⑥

Replace ▼ with option code.
 See page F103 for
 factory installed modifications

Contactor Electronic DC Coil Codes (*) ④

DC Coil Codes	Voltage
12E	12V
24E	24V
36E	36-48V
48E	48-72V
110E	110-125V
220E	220-250V

KWIKstarter coils are wired standard from the factory to terminals "L1" and "L2" (for line voltage control). This means the coil voltage must match the line voltage. When a coil is specified for 120V or less, it will be wired for a separate control source (not wired to L1 and L2).

① Horsepower ratings shown in the table above are for reference. The final selection of the controller depends on the actual motor full load current and service factor. For motor with service factor less than 1.15. Use motor nameplate full load current times 0.9 and choose the motor starter with the appropriate current range. Example: Motor FLC = 4.2A; S.F. = 1.0. 4.2A x 0.9 = 3.78A. Select catalog number KTA7-25S-4A.

② Magnetic trip is fixed at 13x the maximum value of the current adjustment range.

③ CXU7 may be applied to single phase loads. Contact factory for these specifications.

④ CXU7-9E...23E with electronic coils are not interchangeable with non-electronic DC or AC coils.

⑤ KAIC Assembly Rating Index. See pages F73-F76 for Application Rating Guide.

⑥ One Pilot Device option must be selected. Blanks are not available. Plastic Bezel is standard. Pilot Device options include D7-BX_ Base Mounted contact blocks. Pilot Light option must match coil voltage 24V AC or DC, 120V AC or 240V AC only. See Section H for more information.

⑦ CPT not possible with KS7-COC4R. Refer to page F118 for wiring diagram and F119 for dimensional information.

⑧ A red and yellow handle may be selected instead of the standard gray and black handle. Change "PG" suffix to "PJ". Ex: Change CXU7-9-10-*AS0.16A-A10-PG▼ to CXU7-9-10-*AS0.16A-A10-PJ▼.

CX7 Non-Reversing Controller Modifications

Pilot Device Options - required		
Select one option only ①②③	Replace ▼ in catalog number with	Price Adder
START-STOP Multi-function	3U	Standard
I-O Multi-function	4U	Standard
OFF-ON 2-Position Selector switch	6	Standard
HAND-OFF-AUTO 3-Position Selector switch	7	Standard
Run Pilot Light Green	1G	Standard
Run Pilot Light Red	1R	Standard
Overload Alarm Pilot Light	1Y	Standard
D7-N8 22mm Hole Plug	0	Standard
Additional KT7 Auxiliaries & Trip Contacts		Change "-A10" to...
Front Mount 300V maximum		
1 NO + 1 NC Auxiliary	-A11	63.36
2 NO Auxiliaries	-A20	63.36
1 NO SC+OL + 1 NC Auxiliary	-T10A01	80.74
1 NO SC+OL + 1 NO Auxiliary	-T10A10	80.74

CX7 Non-Reversing Controller Additions

Addition	Add to end of catalog number	Price Adder
CA7 Contactor Accessories		
Electronic Interface ④	-JE	96.07
Surge Suppressor RC	-C	55.19
Surge Suppressor Varistor	-V	55.19
CA7 Auxiliary Contacts ⑤⑥		
1 NO Auxiliary	-S10 ⓧ	45.99
1 NC Auxiliary	-S01 ⓧ	45.99
1 NO + 1 NC Auxiliary	-S11	58.25
2 NO Auxiliaries	-S20	58.25
2 NC Auxiliaries	-S02	58.25
Alternate Aux. Contact Arrangement (CA7 only)		
1 NC in lieu of standard 1 NO	-SX10	17.37
2 NC in lieu of standard 2 NO (on CXU7 only)	-SX2	17.37
Unwired Terminal Blocks Specify quantity (▼)	-▼TB	22.48

CXU7 Reversing Controller Modifications

Pilot Device Options - required		
Select one option only ①②③	Replace ▼ in catalog number with	Price Adder
FOR-STOP-REV Multi-function	3U	Standard
UP-STOP-DOWN Multi-function	4U	Standard
OPEN-STOP-CLOSE Multi-function	5U	Standard
FOR-STOP-REV 3-Position Selector switch	6	Standard
UP-OFF-DOWN 3-Position Selector switch	7	Standard
OPEN-OFF-CLOSE 3-Position Selector switch	8	Standard
Overload Alarm Pilot Light	1Y	Standard
D7-N8 22mm Hole Plug	0	Standard
Additional KT7 Auxiliaries & Trip Contacts		Change "-A10" to...
Front Mount 300V maximum		
1 NO + 1 NC Auxiliary	-A11	63.36
2 NO Auxiliaries	-A20	63.36
1 NO SC+OL + 1 NC Auxiliary	-T10A01	80.74
1 NO SC+OL + 1 NO Auxiliary	-T10A10	80.74

CXU7 Reversing Controller Additions


Addition	Add to end of catalog number	Price Adder
CA7 Contactor Accessories		
Electronic Interface ④	-JE	192.14
Surge Suppressor RC	-C	110.38
Surge Suppressor Varistor	-V	110.38

① KS7-C0C4R only has (1) 22mm hole to accommodate (1) pilot device.
 ② Currently supply D7 multi-function pushbuttons as standard which do not require protective boots to meet Type 4X.
 See Section H in this catalog for description (all suffix's ending in "U").
 ③ Pilot Lights may be applied with 24VAC/VDC, 120VAC or 240VAC Control Circuit. Pilot Lights with 380 VAC...575VAC require a control circuit transformer.




④ CRI7E-24 will be used. CRI7E-12 by special order only.
 ⑤ See page A47 for limitations on adding auxiliaries to Electronic DC Coil contactors.
 ⑥ Additional auxiliaries are per contactor. Number of auxiliaries is double for reversing applications. Multiply price adder by two (2).

F Enclosed Motor Circuit Controllers




CX7 KWIKstarter Enclosures for use with KTA7 Type E Motor Controllers and CA7 Contactors ①③

Component	Description	For Use With		Environmental Approvals	Catalog Number	Price
		Type E Controller	Contactors			
	Enclosure for Combo KWIKstarter ① CX7/CXU7-9...23 CX7/CXU7-9E...23E	KTA7-25S KTA7-25H	CA7-9...23 CA7-9E...23E CAU7-9...23 CAU7-9E...23E	cUL Type 1/12K IEC IP66	KS7-C0C4R	103.22

Handle Accessory for CX7/CXU7 KWIKstarters ①

Accessory	Description	For Use With	Color	Catalog Number	Price
	Door Coupling Handle ① • Padlockable • NEMA Type 1/12K and IP66 • Includes handle coupling (shaft) • Requires KT7-KN1 Locking Knob	All KT7s	Gray/Black	KT7-SHB	18.40
			Red/Yellow	KT7-SHBY	18.40
	Lockable Twist Knob • for use with KT7-SHB	All KT7s	Gray/Black	KT7-KN1	See page F16
	Universal Connector for CX7/CXU7 • Provides electrical interconnection of KTA7 and CA7 (with AC or Electronic DC coil) • Applies to FVNR and FVR versions • Allows for mounting the CA7 on a single DIN rail	All KT7s	Black	KT7-25S-PEC23A ④	35.77

CX7 KWIKstarter Pilot Device Kits (for use with KS7-C0C4R Type 1/12K) ①②

Kits	Description	Contact Blocks included		Catalog Number	
		NO	NC		
	Multi-Function Pushbutton kit Non-illuminated START-STOP I-O	1	1	KS7-P3U KS7-P4U	See page C29 for
	FOR-STOP-REV UP-STOP-DOWN OPEN-STOP-CLOSE	2	1	KS7-P3U-REV KS7-P4U-REV KS7-P5U-REV	
	Selector switch kits Non-illuminated, includes legend plate				
	ON-OFF 2-Position	1	0	KS7-P6	
	HAND-OFF-AUTO 3-Position	2	0	KS7-P7	
	FOR-OFF-REV 3-Position UP-OFF-DOWN 3-Position OPEN-OFF-CLOSE 3-Position	2	0	KS7-P6-REV KS7-P7-REV KS7-P8-REV	
	Run Pilot Light or Overload Alarm Pilot Light Plastic operator with diffuser lens in Red, Green or Yellow, with integrated LED power module		Replace ⑤ with color choice R = Red G = Green Y = Yellow	KS7-P1 ②24V ⑥ KS7-P1 ②120V KS7-P1 ②240V	
	Hole Plug used to plug 22.5mm holes.		Gray Plastic	D7-N8	See page H72

① KS7-C0C4R is supplied with the following holes:
• (1) one 22mm hole for a Pilot Device option, select one kit from this page.
• (1) one 22mm hole for KT7-SHB (or SHRY) Disconnect or Reset handle.

② Plastic bezel is standard. Pilot Device Kits include D7-BX_ Base Mounted contact blocks. See Section H for more information.

③ CPT not possible.

④ Standard KT7-25S-PEC23 does not work in CX7/CXU7 Kwikstarters.

⑤ KS7-P1 ②24V can be used with 24VAC or 24VDC.

F Enclosed Motor Circuit Controllers